

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
4 March 2004 (04.03.2004)

PCT

(10) International Publication Number
WO 2004/019512 A1

(51) International Patent Classification⁷: **H04B 3/14**
(21) International Application Number:
PCT/BE2003/000140
(22) International Filing Date: 20 August 2003 (20.08.2003)
(25) Filing Language: English
(26) Publication Language: English
(30) Priority Data:
02447160.9 22 August 2002 (22.08.2002) EP
(71) Applicant (for all designated States except US): **VRIJE
UNIVERSITEIT BRUSSEL [BE/BE]**; Pleinlaan 2,
B-1050 BRUSSELS (BE).

(81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.

(84) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).


(72) Inventor; and
(75) Inventor/Applicant (for US only): **KUIJK, Maarten**
[BE/BE]; Vredestraat 154, B-2600 BERCHEM -
ANTWERPEN (BE).

(74) Agents: **VAN MALDEREN, Joëlle et al.**; Office Van
Maldereen, Place Reine Fabiola 6/1, B-1083 Brussels (BE).

Published:
— with international search report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: **ADAPTIVE EQUALIZER**



(57) Abstract: The present invention is related to an adaptive equalizer comprising : an equalizer filter (32) for filtering a distorted signal from a communication channel, having a data input (30) for receiving said distorted signal, a feedback signal input for a feedback control signal, and which generates an output signal at an output node (35); circuitry (46) for processing said output signal and generating said feedback control signal, the circuitry comprising a first means (38) for measuring a short-term-amplitude signal of said output signal, a second means (38) for measuring a long-term-amplitude signal of said output signal, a comparator means (43) that compares said short-term-amplitude signal and said long-term-amplitude signal and that determines the evolution of said feedback control signal, arranged such that said distorted signal is compensated for its higher frequency attenuation in said communication channel.

BEST AVAILABLE COPY

5

ADAPTIVE EQUALIZER**Field of the invention**

- 10 [0001] The present invention relates to an adaptive line equalizer and more specifically to the related feedback control system employed to compensate for the attenuation of signals transmitted over a communication channel.

15

State of the art

- [0002] Adaptive equalizers generally include a variable filter, a control loop and an output reconstruction unit.
- 20 [0003] US patent 3,728,649 compares the differentiated and peak detected pulse output of a variable equalizer to an output level of a reference voltage source to produce a feedback control signal.
- [0004] US patent 5,796,778 describes a circuit that
- 25 has an equalizer circuit and a variable gain amplifier circuit.
- [0005] US patent 5,940,442 achieves equalization by monitoring the peak-to-peak amplitude, amplitude peaks and differences between amplitude peaks of the equalized data
- 30 signal during defined time intervals.
- [0006] However, none of the present state-of-the-art adaptive equalizers have a satisfactory control feedback method that functions well for a large range of transmit amplitudes and of transmit data patterns. The robustness

against process-parameter changes is insufficient in most proposed solutions, limiting the production yield of such circuits.

5 Aims of the invention

[0007] The present invention aims to provide a novel equalizer design which provides an optimised equalisation of signals transmitted over a communication channel, and more particularly to compensate for the attenuation of said
10 signals.

Summary of the invention

[0008] In a first and second aspect of the present invention, a method and a circuit to generate a feedback
15 control signal that is generated from the equalized output of the equalizer filter before it is digitised are disclosed. Depending on whether the signal has been under- or over compensated, said feedback control signal will increase or decrease, such that after reasonable time the
20 feedback control signal will converge to a value where optimal compensation is reached. The method is applicable for equalizers that restore as well DC-balanced as DC-unbalanced data. An adaptive equalizer according to the present invention would also work for various digital
25 transmit amplitudes. Also, the equalizer functions well for a broad range of transmitted data-patterns. In an embodiment of the present invention, burst mode operation is included. Multiple stage equalization with multiple feedback loops, in order to allow adaptive compensation for
30 a large range of channel lengths and channel types are also disclosed.

[0009] The present invention discloses an adaptive equalizer comprising:

- an equalizer filter for filtering a distorted

signal from a communication channel, having a data signal input for receiving said distorted signal, a feedback signal input for a feedback control signal, and which generates an output signal at an output node;

- circuitry for processing said output signal and generating said feedback control signal, the circuitry comprising

- o a first means for measuring a short-term-amplitude signal of said output signal,

- o a second means for measuring a long-term-amplitude signal of said output signal,

- o a comparator means that compares said short-term-amplitude signal and said long-term-amplitude signal and that determines the evolution of said feedback control signal,

arranged such that said distorted signal is compensated for its higher frequency attenuation in said communication channel.

[0010] Preferably, in such an adaptive equalizer according to the present invention, the short-term-amplitude signal of the output signal is indicative for the amplitude of the high-speed component of said output signal. The long-term-amplitude signal can be indicative for the amplitude of the output signal stripped from its possible overshoot peaks. The short-term-amplitude signal of the output signal can be generated by a circuit comprising a high-pass filter and a peak detector. The long-term-amplitude signal of the output signal can be generated by a circuit comprising a low-pass filter and a peak detector.

[0011] In a preferred embodiment, in the adaptive equalizer of the present invention, said output signal is

fed to a limiting amplifier to produce a digital output signal.

[0012] In another aspect of the present invention, a multi-stage adaptive equalizer is disclosed, comprising at least a first and a second adaptive equalizers such as described higher, wherein the output signal of said first adaptive equaliser is fed to the data input node of said second adaptive equaliser.

The present invention also concerns a method for adaptively equalising a distorted signal comprising high frequency attenuation received from a communication channel, comprising the steps of:

- Filtering said distorted signal and providing an output signal at an output node,
- Comparing a short-term-amplitude signal of said output signal to a long-term-amplitude signal of said output signal to provide a feedback signal, and
- Providing a feedback signal to compensate said high frequency attenuation in said distorted signal.

[0013] In the method according the present invention, the short-term-amplitude signal of the output signal can be indicative for the amplitude of the high-speed component of the output signal. The long-term-amplitude signal can be indicative for the amplitude of the output signal stripped from its possible overshoot peaks.

Short description of the drawings

[0014] Exemplary embodiments of the invention and of the use of the invention are shown in the drawings. The drawings are schematic representations of the invention and therefore the dimensions and the relative dimensions do not correspond to actual reductions to practice of the invention.

[0015] Fig. 1 shows the preferred embodiment of the present invention, including a high-pass filter, low-pass filter and peak detectors in control circuitry.

5 [0016] Fig. 2 is a schematic explanation of the operation of the control circuit, showing the conditions of under-compensation, optimal-compensation, and over-compensation.

[0017] Fig. 3 shows a preferred embodiment of the
10 low-pass filter (a) connected to its peak detector, and the high pass-filter (b) connected to its peak-detector. Both circuits assume differential signal treatment at their input.

[0018] Fig. 4 shows signal evolutions versus time of
15 exemplary nodes in the case that optimal compensation has been reached.

[0019] Fig. 5 shows the cascade of two adaptive equalizers each having their control feedback loop of the present invention allowing adaptation to various channel
20 lengths and types.

Detailed description of the invention

[0020] The invention is described in the sequel through a detailed description of several embodiments of
25 the invention. It is obvious that other embodiments of the invention can be configured according to the knowledge of persons skilled in the art without departing from the true spirit of the invention, the invention being limited only by the terms of the appended claims. It will be clear for
30 the person skilled in the art that the present invention is also applicable to the similar circuits that can be configured in any transistor technology, including, CMOS BICMOS and SiGe BICMOS. Also will it be clear that similar merits of the invention can be obtained when single ended

signals are implemented as differential signals and vice-versa, without departing from the true spirit of the invention.

[0021] Figure 1 shows the preferred embodiment of the present invention. A digital signal that has been transmitted through a communication channel is attenuated in its higher frequency components, and enters the equalizer of the present invention on node 30 being its data input. Communication channels include twisted pair, coax-cable, and printed circuit board transmission lines, including both differential signalling as single ended signalling methods, as is understood by the person skilled in the art. Attenuation of higher frequency components can be due to several attenuation mechanisms including metal skin-effect, dielectric losses and first order attenuation including parasitic capacitances and/or inductances at Printed Circuit Board via's and connectors.

[0022] Node 30 is the input of Filter 32. Filter 32 can be any type of compensation filter that is being controlled by a feedback control signal α , on node 47 and that can be used for equalization. Many filter types in CMOS and BICMOS have been disclosed in patents and literature. Filter 32 has the intention to compensate for the frequency dependent losses that are introduced by the preceding communication channel. The feedback control signal α determines to which extent the higher frequencies will be amplified more than the lower frequencies. A typical implementation of filter 32 includes the use of a stage whereby the input signal is split into a flat response branch and a higher-frequency gain response branch including filter 31, after which, according to the feedback control signal α , more weight can be given to the one than

to the other branch. With α being 0, the flat response branch is selected, with α being 1, maximum compensation is being applied. A value in-between corresponds to an intermediate compensation. Typically, a higher α corresponds to a longer transmission channel. For large compensation values, several of these filter stages can be cascaded using each the same α .

[0023] The more difficult part in adaptive equalization is to organise the feedback loop that regulates α , such that it converges essentially to its optimum value. At a too high α , over-compensation will be present, at a too low α , under-compensation occurs.

[0024] In the present invention, control feedback signal α is determined mainly relying on the equalized signal on node 35, at the output after the equalizer. This signal should not yet be clipped. Therefore care should be taken that in all circumstances the signal is still in its analogue form. Clipping can be done in a later stage, in - for example- a limiting amplifier 36. Alternatives for clipping include bit-slicing, and the use of decision feedback principles, as known by the person skilled in the art.

[0025] From the signal on node 35, a long-term-amplitude signal is generated that is indicative for the amplitude of the signal on node 35 when it would first be stripped from its possible overshoot peaks. A robust way to achieve this intention is by feeding the signal on node 35 into a low pass filter 39 followed by a peak detector 49. The output of this peak detector forms the long-term amplitude signal. It is present as the voltage on node 45.

- [0026] Further from the signal on node 35, a *short-term-amplitude signal* is generated that is indicative for the high-speed component present in the signal on node 35. A robust way to achieve this is by feeding the signal on
5 node 35 into a high-pass filter 38, followed also by a peak-detector 48. The output of this peak detector generates the short-term amplitude signal. It is present as the voltage on node 44.
- 10 The peak detectors 48 and 49 have a relatively long memory effect, such that they can keep their peak-value even when many consecutive same bits are passing. Their respective outputs 44 and 45 are then subtracted and determine the signal change on the loop capacitor C_{loop} 50. In this
15 example, the voltage on this capacitor node 47 then forms the control feedback signal that determines the amount of higher frequency gain of equalizer filter 32. In this way the negative feedback loop is closed.
- 20 [0027] Figure 2 explains more graphically the operation principle on a bit-sequence 0110. At the left, a situation of under-compensation is assumed, at the right, over-compensation, and in the middle, the optimal-compensated state is assumed. If there is under-
25 compensation of the higher frequencies, the peak value of the signal after high-pass Ph is smaller than the peak signal after low-pass Pl. The result is that the signal after the peak detector on node 44 is lower than the signal after the peak-detector on node 45. Hence α will increase.
- 30 Conversely, when there is over-compensation of the higher frequencies, the peak value Ph of the signal after high-pass will be higher than the peak signal Pl after low-pass. The result is that the signal after the peak detector on

node 44 is then higher than the signal after the peak-detector on node 45. In other words, the short-term-amplitude signal is larger than the long-term amplitude signal. Hence α will decrease. The low-pass filter 39 and
5 high-pass filter 38 are further organised such that when optimal compensation is reached, the signals on node 44 and node 45 become essentially equal.

When the transmit-amplitude is increased, both peak values
10 will increase accordingly and in the same amount, and the system is still corresponding correctly, i.e. it will remain converging to the optimal state. For this to be true we assume that the filters behave linearly and that not any unwanted saturation effect is present in these
15 circuits. In this way good operation is achieved independent on the transmit amplitude at the sender side. The principle remains operative for both DC-balanced and DC-unbalanced data.

20 [0028] The -3dB frequency for the low-pass filter 39 is preferably targeted below or at the highest frequency of the incoming data. For a 3.2 Gbit/s, the highest signal frequency is 1.6 GHz, and the -3dB frequency of the low-pass filter is suggested to be chosen at or below 1.6 GHz.
25 E.g., 1-GHz is a nice target in this case. The exact value is not so important, since the peak detector 49 will settle on longer strings of consecutive same symbols when this frequency-value is lower. Important here is that overshoots that are occurring when having over-compensation are
30 essentially filtered out by the low-pass filter.

[0029] The -3dB frequency of the high-pass filter 38 should be targeted preferably below the highest expected

signal frequency. For 3.2 Gbit/s, also 1 GHz is a good value. It can be shown that, in this way the peak amplitude that is monitored by the peak detector depends less on the precise -3dB frequency position, and more on the resistor values in the filter. Fortunately, these resistor values change in the same way as the resistor values of the low-pass filter 39 change, assuming that the resistors in filters 38 and 39 are of the same type and are as such depending simultaneously on process fluctuations. In this way the state to which the feedback loop converges becomes relative independent on changes in process parameters of capacitors and resistors.

[0030] Figure 3 shows circuits that perform these low- and high-pass functions together with their peak detector circuits in the case of differential input signals. The person skilled in the art can recognize a first order low-pass filter in figure 3 a, followed by a peak-detecting circuit. The low-pass filter includes transistors M10, M11, resistors Ra, Rb & Rc, capacitor Ca and current sources I1 and I2. It is preferably made symmetric, as is understood by the person skilled in the art. The outputs of the filter are coupled to two emitter-followers M12 and M13 that operate as peak detectors. For this to be true, current source I3 needs to sink only a small current such that capacitor Cb will hold the peak value during a large multitude of bit-times. Due to the emitter followers a shift of approximately 800 mV will be present between the peak values on the output nodes and on the value P1 at the output of the peak detector. This is not a concern assuming the high-pass filter in the lower part of the figure is designed very similar and with similar values as the low-pass filter. Both will then show

the same voltage drop of 800 mV and this will cancel out at the comparator.

[0031] The high-pass filter with connected peak detector in figure 3b is very similar to the low-pass filter. All values of current-sources and resistors can be very much the same. Only the position and the value of the capacitor C_c , and C_a are different. The person skilled in the art can easily calculate, design and simulate which values all components optimally have, depending on the specification of its circuits. Hereby, care should be taken that convergence to essentially the optimal compensation situation is reached.

[0032] Figure 4 shows the associated signal evolution of the filtering operation when having reached convergence to optimal compensation. Curves 101 and 102 represent a differential input signal that will be the input for the two filters. Curves 103 and 104 represent the resultant differential output signal (on differential node 41) after the low-pass filter. The highest frequency oscillations (e.g. at about 80 ns) are somewhat attenuated. The peak value is at about 2.85 Volt and is tracked by the peak detector signal, offset by 800 mV, giving curve 105. The voltage value after the peak detector is about 2.05 volt.

[0033] Curves 106 and 107 represent the differential output signal (on differential node 40) after the high-pass filter. The peak values at 2.85 Volt are followed by the peak detector signal, offset by 800 mV, giving curve 108, also at 2.05 volt.

[0034] When not being at the point of optimal compensation, it is clear that the relative voltages of the

peak detector outputs will change. In the over-compensation case, the peaks in the curves 106 and 107 will become higher, such that curve 108 will be at a higher voltage as well. In the under-compensation case, the peaks in the
5 curves 106 and 107 will become lower, such that curve 108 will consequently evolve to a lower voltage.

[0035] When envisaging operation whereby very long strings of consecutive same symbols are present in the data
10 stream, it is advised to detect that this is occurring, and then inhibit the loop capacitor C_{loop} 50 to change voltage. This can easily be achieved, by putting a switch in-between the output of OTA 43 and said capacitor 50. To determine when such long strings are passing is known by the person
15 skilled in the art. By inhibiting the updating of the voltage on capacitor C_{loop} 50, the equalizer becomes ready for burst-mode operation.

[0036] The attenuation behaviour versus frequency in
20 a communication channel for a given channel length depends largely on the mechanisms that form the basis for the attenuation. E.g. attenuation due to skin effect will be clearly less steep than attenuation due to dielectric losses or due to parasitic capacitance or inductance. When
25 having only a one parameter adaptive equalizer, one has to assume a given attenuation behaviour for the design of the filter 31. However, with the findings of the present invention, it finally becomes possible to make a two-parameter adaptive equalizer. This is disclosed in figure
30 5. Two similar stages present in Figure 1 are connected in series, each of the stages having their own feedback loop. Preferably, the first stage regulates slower transitions, e.g. for sequences with multiple consecutive same bits. The

-3dB transition frequencies in the filters 38 and 39, are then at a two to ten times lower frequency than when having a system based on only one control feedback loop. The -3dB frequencies of filters 58 and 59 of the second loop remain
5 preferably targeted at the same frequency values as when having a system based on only one control feedback loop.

[0037] Example given, when targeting 3.2 Gbit/s operation, -3dB frequencies of the filters 38 and 39 can be
10 at 400 MHz, while filters 58 and 59 can be at 1 GHz. It is advised that equalizing filter 31 would then compensate in the full frequency range, and equalizing filter 51 would compensate mainly at the higher frequencies, for this example from 500 MHz to 2 GHz.

15

[0038] It is also an option to design equalizing filter 31 for skin-effect losses, and equalizing filter 51 for dielectric losses and first order parasitic attenuation effects. The final digitising stage can still be of any
20 type that would work with a one-parameter system, including a limiting amplifier as is suggested in figure 5 by block 36. It is advised not to digitise in-between the two stages of the equalizer, but only after the last stage. With such two-parameter system it is expected that a larger range of
25 cable types and attenuation sources can be compensated, resulting in better jitter behaviour for various channel media. Possibly it can become useful to make more than two loops. Similar principles can then be used as for the explained two-stage situation. Burst mode operation can
30 also become possible on multiple parameter systems. The same disconnection principle can be used as for the single parameter solution explained above, however now applied to each of the control feedback loops.

CLAIMS

1. . An adaptive equalizer comprising:

- an equalizer filter (32) for filtering a distorted signal from a communication channel, having a data
5 signal input (30) for receiving said distorted signal, a feedback signal input for a feedback control signal, and which generates an output signal at an output node (35);
 - circuitry (46) for processing said output signal
10 and generating said feedback control signal, the circuitry comprising
 - o a first means (38) for measuring a short-term-amplitude signal of said output signal,
 - o a second means (38) for measuring a long-term-amplitude signal of said output signal,
15 o a comparator means (43) that compares said short-term-amplitude signal and said long-term-amplitude signal and that determines the evolution of said feedback control signal,
- 20 arranged such that said distorted signal is compensated for its higher frequency attenuation in said communication channel.

2. An adaptive equalizer such as in claim 1, wherein the short-term-amplitude signal of the output
25 signal is indicative for the amplitude of the high-speed component of said output signal.

3. An adaptive equalizer such as in claim 1 or 2, wherein the long-term-amplitude signal is indicative for the amplitude of the output signal stripped from its
30 possible overshoot peaks.

4. An adaptive equalizer such as in any of the claims 1 to 3, wherein the short-term-amplitude signal

of the output signal is generated by a circuit comprising a high-pass filter and a peak detector.

5 5. An adaptive equalizer such as in any of the claims 1 to 4, wherein the long-term-amplitude signal of the output signal is generated by a circuit comprising a low-pass filter and a peak detector.

6. An adaptive equalizer such as in any of the claims 1 to 5, wherein said output signal is fed to a limiting amplifier (36) to produce a digital output signal.

10 7. An multi-stage adaptive equalizer comprising at least a first and a second adaptive equalizers such as in any of the claims 1-5, wherein the output signal of said first adaptive equaliser is fed to the data input node of said second adaptive equaliser.


15 8. A method for adaptively equalising a distorted signal comprising high frequency attenuation received from a communication channel, comprising the steps of:

- Filtering said distorted signal and providing an output
20 signal at an output node,
- Comparing a short-term-amplitude signal of said output signal to a long-term-amplitude signal of said output signal to provide a feedback signal, and
- Providing a feedback signal to compensate said high
25 frequency attenuation in said distorted signal.


9. The method as in claim 8, wherein the short-term-amplitude signal of the output signal is indicative for the amplitude of the high-speed component of the output signal.

30 10. The method as in claim 8 or 9, wherein the long-term-amplitude signal is indicative for the amplitude of the output signal stripped from its possible overshoot peaks.

1/5


**FIG. 1**

2/5

**FIG. 2**


3/5

FIG. 3




4/5

FIG. 4



5/5

FIG. 5



INTERNATIONAL SEARCH REPORT

Intern Application No
PCT/BE 03/00140

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H04B3/14

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, PAJ, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 4 531 165 A (SONU GENE H ET AL) 23 July 1985 (1985-07-23) column 3, line 26-35; figure 4 column 5, line 9-15 column 4, line 9-27	1-5,7-10
A	US 4 250 459 A (HAASS ADOLF) 10 February 1981 (1981-02-10) column 4, line 4-49; figures 1,2	1-10
A	US 5 442 328 A (HALIN PIERRE) 15 August 1995 (1995-08-15) column 4, line 18 -column 5, line 49; figure 3A	1-10



Further documents are listed in the continuation of box C.



Patent family members are listed in annex.

* Special categories of cited documents :

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *8* document member of the same patent family

Date of the actual completion of the international search

31 October 2003

Date of mailing of the international search report

07/11/2003

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Amorotti, M

INTERNATIONAL SEARCH REPORT

Information on patent family members

Intern . Application No

PCT/BE 03/00140

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 4531165	A	23-07-1985	DE 3477706 D1	18-05-1989
			EP 0139925 A1	08-05-1985
			JP 1763541 C	28-05-1993
			JP 4058112 B	16-09-1992
			JP 60079566 A	07-05-1985
US 4250459	A	10-02-1981	DE 2810504 A1	13-09-1979
			AT 372809 B	25-11-1983
			AT 173779 A	15-03-1983
			BR 7901429 A	09-10-1979
			CA 1137180 A1	07-12-1982
			DE 2960471 D1	22-10-1981
			DK 98279 A , B	11-09-1979
			EP 0004054 A1	19-09-1979
			MX 146561 A	07-07-1982
			NO 790787 A , B,	11-09-1979
US 5442328	A	15-08-1995	FR 2685832 A1	02-07-1993
			DE 69220022 D1	03-07-1997
			DE 69220022 T2	02-10-1997
			EP 0550316 A1	07-07-1993

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

☐ BLACK BORDERS

☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES

☐ FADED TEXT OR DRAWING

☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING

☐ SKEWED/SLANTED IMAGES

☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS

☐ GRAY SCALE DOCUMENTS

☒ LINES OR MARKS ON ORIGINAL DOCUMENT

☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY

☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.